

B&E Technologies

FE-050T / FE-050C 100FX 10/100TX to 100FX switch based media converters.

The 10/100BASE-TX to 100BASE-FX media converter series provides a media conversion allowing high-speed integration of fiber optic and twisted pair segments. With 10BASE-T and 100BASE-TX support, the converters provide seamless translation between Ethernet and Fast Ethernet networks. A complete set of LEDs allows for quick status verification.

Converter Features

- Convert speed and media type
- Support full wire speed conversion
- Support 10Mbps and 100Mbps speed on TP connections
- Auto MDI/MDI-X detection function on the TP port
- Auto-negotiation function on the TP port
- Link fault pass through function
- Provide manual configuration settings for TP port to support connection to non-auto negotiation devices
- Transparent to 802.1Q VLAN tagged packets
- Far End Fault function on FX port
- Provide LED status display for remote TP port monitoring
- Provide Loop Back Test function for installation diagnostics
- Support wide range of fiber options on the FX port
- Low power consumption

Operating Environment

- Operating Input Voltages: +4.75V ~ +12.6V
- Power consumption: 2W max. (0.27A@+7.5V)
- Operating Temperature: -5°C to 40°C
- Storage Temperature: -20°C to 85°C
- Operating Humidity: 10% to 90% (non-condensing)
- Storage Humidity: 5% to 90% (non-condensing)

Warranty

- 2 years



B&E TECHNOLOGIES
8 Victoria Glen Street
Elmira, Ontario Canada
N3B 1S1
Phone: 519 669 0950
Fax: 519 669 2880
info@betech.biz
www.betech.biz