

# B&E Technologies

## E-104TP 10base-T Ethernet Adapter for ISA Bus

This is a 16-bit Ethernet NE2000 compatible Adapter for the ISA bus. It supports jumper-less configuration with an easy to use configuration program. It also supports Plug and Play configuration. A single jack connects to unshielded twisted pair (UTP) network cabling. The adapter is supplied with a QNX network driver. A QNX network boot ROM is also available.



### LAN Interface

- 8/16 bit ISA bus
- 10Mbps transmission rate
- NE2000 compatible
- Full or half duplex auto negotiation
- I/O mapped (Can be set in the range from 200 to 3E0 in increments of 20)
- Interrupts (2, 3, 4, 5, 10, 11, 12, 15)
- ROM: Optional Boot ROM
- RAM: 16KB packet buffer
- Jumper-less NE2000 configuration
- Configuration via PnP BIOS or supplied QNX setup programs
- Uses NE2000 drivers

### Operating Environment

- Power: +5V DC @ 0.5A max.
- Operating Temperature: 0°C to 55°C
- Storage Temperature: -40°C to 70°C
- Operating Humidity: 10% to 90% (non-condensing)
- Storage Humidity: 5% to 90% (non-condensing)

# *Product Specifications*

## **Physical Specifications**

- PCB mounted low profile RJ-45
- LED indicator for link status: indicates link is operating normally
- Dimensions: 157mm x 60mm (6.18" x 2.36")

## **Warranty**

- 2 years

## **Cabling**

- Category 3 or better unshielded twisted pair
- Distance from node to hub: 100m (325 ft)

## **ALSO AVAILABLE**

CT-E001 QNX Boot ROM

B&E TECHNOLOGIES  
8 Victoria Glen Street  
Elmira, Ontario Canada  
N3B 1S1  
Phone: 519 669 0950  
Fax: 519 669 2880  
[info@betech.biz](mailto:info@betech.biz)  
[www.betech.biz](http://www.betech.biz)